

















PLATINUM SERIES

8-Way HDMI® Splitter with Signal Booster & EDID Control

AVC-PS128

EDID DIP Switch Chart

Mode	8421 / BCD		Physical		EDID Information Resolution / Colour Depth / Audio Format
	Binary Code	DIP 4 3 2 1	DIP Position	DIP 1 2 3 4	
1	1111	↑↑↑↑		↑↑↑↑	4Kx2K/60Hz, 24bit, 2D, 2.0CH
2	1110	↑↑↑↓		↓↑↑↑	1080p/60Hz, 24bit, 3D, 2.0CH
3	1101	↑↑↓↑		↑↓↑↑	1080p/30Hz, 1080i/60Hz 720p/60Hz, 24bit, 2D, 2.0CH
4	1100	↑↑↓↓		↓↓↑↑	1080p/30Hz, 1080i/60Hz 720p/60Hz, 24bit, 2D, 7.1CH
5	1011	↑↓↑↑		↑↑↓↑	1080p/60Hz, 36bit, 2D, 2.0CH
6	1010	↑↓↑↓		↓↑↓↑	1080p/60Hz, 36bit, 2D, 7.1CH
7	1001	↑↓↓↑		↑↓↓↑	1080p/60Hz, 24bit, 2D, 2.0CH
8	1000	↑↓↓↓		↓↓↓↑	1080p/60Hz, 24bit, 2D, 7.1CH
9	0111	↓↑↑↑		↑↑↑↓	Copy Output 1
10	0110	↓↑↑↓		↓↑↑↓	Copy Output 2
11	0101	↓↑↓↑		↑↓↑↓	Copy Output 3
12	0100	↓↑↓↓		↓↓↑↓	Copy Output 4
13	0011	↓↓↑↑		↑↑↓↓	Copy Output 5
14	0010	↓↓↑↓		↓↑↓↓	Copy Output 6
15	0001	↓↓↓↑		↑↓↓↓	Copy Output 7
16	0000	↓↓↓↓		↓↓↓↓	Compose Downscale

Note: Compose Downscale uses the lowest compatible audio format and offers downscaling for non-4K displays. At least two displays must be connected and the input must be 4K@60Hz 4:4:4 or 4:2:0 (HDR10) for Downscaler function.

For more information, please visit www.avencore.com.au